

Everygy Approved Residential Meter Sockets

Revision Date: 8/26/2025

120/240V or 120/208V Single Phase				
Socket Size/Type	Milbank	Durham ¹	Talon	Eaton
1 gang, 100A, 3-wire	U7043-XL-TG-KK-IL-5T9W	1010291	UAT817-XVZKCPL	UGHTRS233CCH
1 gang, 200A, 3-wire ²	U7043-XL-TG-KK-IL-5T9W	1010291	UAT817-XVZKCPL	UGHTRS233CCH
1 gang, 400A, 3-wire	U4702-X-5T9-K3-K2-IL	UG-H4300U-KC	47705-82KCPL	
1 gang, 400A, 3-wire	U2448-X-5T9-K3-K2-IL			

Generation Meter Can Only ⁶			
Socket Size/Type	Milbank	Durham ¹	Talon
1 gang, 100A, 3-wire	U5934-XL-BLG w/K5T kit ³	-	-
1 gang, 200A, 3-wire	U7043-XL-TG-KK-IL-5T9W ⁷	1010291 ⁷	UAT817-XVZKCPL ⁷
1 gang, 200A, 3-wire	U9801-RXL-GEN-TAP-5T9-EVE ³		
1 gang, 400A, 3-wire	U4702-X-5T9-K3-K2-IL w/K5979 kit ³	UG-H4300U-KC ⁷	47705-82KCPL ⁷

120/240V Horizontal Gang Sockets (No Breakers)			
Socket Size/Type	Milbank	Durham ¹	Talon
2 gang, 100A, 3-wire	U1232-X-5T-K1	UG-2R5332C-KC	UA2311-XB
3 gang, 100A, 3-wire	U1233-X-5T-K3	UG-3R1131C-KC	UA3311-XB
4 gang, 100A, 3-wire	U1234-X-5T-K3	-	UA4311-XB
2 gang, 200A, 3-wire	U1252-X-5T-K1	UG-2R2332U-KC	UA2716-ZB
3 gang, 200A, 3-wire	U1253-X-5T-K1	-	UA3717-ZB
4 gang, 200A, 3-wire	U1254-X-5T-K4	-	UA4719-ZB
5 gang, 200A, 3-wire	U1255-X-5T-K4	-	UA5719-MB
6 gang, 200A, 3-wire	U1256-X-5T-K4	-	UA6719-MB

Meter Packs - 120/240V Condominium/Apartment Sockets (For Applications of 6 or LESS)					
Socket Size/Type	Milbank	Cutler Hammer	Square D	GE	Siemens
2 gang 125A, 3-wire	U2852-X-KK-5T	1MP3124RRL w/ 1-1MMPCP	MRP33125 w/Closing Plate	TMMR2212RHB	WP2211RJB
	U5902-X-KK-K4-5T-KCPL ⁴				
3 gang 125A, 3-wire	U2853-X-KK-5T	1MP4124RRL w/ 1-1MMPCP	MPR33125	TMMR4312RHB	WP3311RJB
	U5903-X-KK-K4-5T-KCPL ⁴				
4 gang 125A, 3-wire	U2854-X-KK-5T	1MP5126RRL w/ 1-1MMPCP	MPR55125	TMMR4412RHB	WP4411RJB
	U5904-X-KK-K4-5T-KCPL ⁴				
5 gang 125A, 3-wire	U2855-X-KK-5T	1MP5126RRL w/ 1-1MMPCP	MPR55125 w/Closing Plate	TMMR6512RHB	WP4511RJB
	U5905-X-KK-K4-5T-KCPL ⁴				
6 gang 125A, 3-wire	U2856-X-KK-5T	1MP6126RRL	MPR66125	TMMR6612RHB	WP6611RJB
	U5906-X-KK-K4-5T-KCPL ⁴				
2 gang 200A, 3-wire	U2862-X-KK-5T	1MP3206RRL w/Closing Plate	MPR42200	TMMR4220RHB	WP4212RJB
	U5882-X-KK-K4-5T-KCPL ⁴				
3 gang 200A, 3-wire	U2863-X-KK-5T	1MP4206RRL w/ 1-1MMPCP	MPR43200	TMMR6320RHB	WP4312RJB
	U5883-X-KK-K4-5T-KCPL ⁴				
4 gang 200A, 3-wire	U2864-X-KK-5T	1MP5126RRL w/ 1-1MMPCP	MPR85200 w/Closing Plate	TMMR6420RHB	WP4412RJB
	U5884-X-KK-K4-5T-KCPL ⁴				
5 gang 200A, 3-wire	U2865-X-KK-5T	1MP5206RRL	MPR85200	TMMR6520RHB	WP6512RJB
	U5885-X-KK-K4-5T-KCPL ⁴				
6 gang 200A, 3-wire	U2866-X-KK-5T	1MP6206RRL	MPR86200	TMMR6620RHB	WP6612RJB
	U5886-X-KK-K4-5T-KCPL ⁴				

Modular Meter Sockets ⁵ - 120/240V Condominium/Apartment Sockets (For Applications of 6 or MORE)			
Socket Size/Type	Square D	ABB	Siemens
2 gang 125A, 3-wire	EZMR113125 W/Closing Plate	RMS18212LHBR	WMM21125RJB
3 gang 125A, 3-wire	EZMR113125	RMS18312LHBR	WMM31125RJB
4 gang 125A, 3-wire	EZMR114125	RMS18412LHBR	WMM41125RJB
2 gang 200A, 3-wire	EZMR112225	RMS18222LHBR	WMM21225RJB
3 gang 200A, 3-wire	EZMR113225	RMS18322LHBR	WMM31225RJB
4 gang 200A, 3-wire	EZMR114225	RMS18422LHBR	WMM41225RJB

Modular Meter Sockets ⁵ - 120/208V Condominium/Apartment Sockets (For Applications of 6 or MORE)		
Socket Size/Type	Cutler Hammer	ABB
2 gang 125A, 3-wire	3MM212RRL	RMS28212LHBR
3 gang 125A, 3-wire	3MM312RRL	RMS28312LHBR
4 gang 125A, 3-wire	3MM412RRL	RMS28412LHBR
2 gang 200A, 3-wire	3MM220RRL	RMS28222LHBR
3 gang 200A, 3-wire	3MM320RRL	RMS28322LHBR
4 gang 200A, 3-wire	3MM420RRL	RMS28422LHBR

Notes

¹ Durham also manufactures these meter sockets branded for Square D Company, Cutler Hammer Inc., and Midwest Electric Products. For these brands add "SOD", "CH", "GE" or "MEP", respectively, as a suffix to the listed Durham catalog number. Except for the additional suffix, all other numbers must match what is in the Durham column, as these are the only approved sockets by these manufacturers.

² Most common residential meter socket options

³ Meter socket has the ability to isolate the neutral lugs from meter enclosure

⁴ NEC 2020 / UL 67 compliant model. Check local jurisdiction for requirements

⁵ Meter Centers require a main disconnect ahead of the socket gangs.

⁶ Verify the meter socket meets the installation requirements and the NEC.

⁷ Meter socket does not have the ability to isolate the neutral lugs from meter enclosure

Evergy Approved Commercial Meter Sockets

Revision Date:

8/26/2025

120/240V Single Phase			
Socket Type	Milbank	Durham ¹	Talon
1 gang, 100A, 3-wire	U9551-RXL-5T9-IL	T-H5213B	48805-0BNU
1 gang, 200A, 3-wire	U9551-RXL-5T9-IL	T-H5213B	48805-0BNU
1 gang, 400A, 3-wire	U4702-X-5T9-K3-K2-IL	UG-H4300U-KC	47705-82KCPL
1 gang, 400A, 3-wire	U2448-X-5T9-K3-K2-IL		

240/480V Grounded B Phase Delta		
Socket Type	Milbank	Durham ¹
1 gang, 200A, 3-wire	U9551-RXL-5T9-IL	T-H5213B

120/208V or 277/480V Commercial Self-Contained Socket (Three Phase)			
Socket Type	Milbank	Durham ¹	Talon
1 gang, 200A, 4-wire	U9701-XL-IL-EVE	U-H7213C-KC	40607-025
1 gang, 400A, 4-wire	U4013-X-2/K7-IL	-	48707-02

Meter Packs- 120/240V (For Applications of 6 or LESS)	
Socket Type	Milbank
2 gang, 200A, 4-wire	U2872-XT-5T9
3 gang, 200A, 4-wire	U2873-XT-5T9
4 gang, 200A, 4-wire	U2874-XT-5T9
5 gang, 200A, 4-wire	U2875-XT-5T9
6 gang, 200A, 4-wire	U2876-XT-5T9

Modular Meter Sockets ⁵ - 120/208 Commercial Self-Contained Socket					
Socket Type	Cutler Hammer	Square D	Talon	GE	Siemens
1 gang, 200A, 4-wire	37MM120R12	EZML331225	WTG2211RJ	TMPR31212	WML13225RJB
2 gang, 200A, 4-wire	37MM220R12	EZML332225	WTG3211RJ	TMPR31222	WML23225RJB
3 gang, 200A, 4-wire	37MM320R12	EZML333225	WTG4211RJ	TMPR31232	WML33225RJB
4 gang, 200A 4-wire	37MM420R12	EZML334225	WTG6211RJ	TMPR31242	WML43225RJB

Notes

¹ Durham also manufactures these meter sockets branded for Square D Company, Cutler Hammer Inc., and Midwest Electric Products. For these brands add "SOD", "CH", GE or "MEP", respectively, as a suffix to the listed Durham catalog number. Except for the additional suffix, all other numbers must match what is in the Durham column, as these are the only approved sockets by these

⁵ Meter Centers require a main disconnect ahead of the socket gangs.

All commercial meter sockets require lever bypass

Evergy Meter-Mains / Meter-Load Center Sockets & Pedestals

Revision Date:

8/26/2025

≤ 200A Residential Meter-Mains and Meter-Load Centers (Horn Bypass)						
Milbank/Siemens/Eaton	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
U5168-XL-100-KK-IL-5T9W-EVE / MC0816B1100RJBT	200A	1Ø3W	100A	10 (with feed- through lugs)	OH/UG	3" Bottom KO; Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; 9" minimum clearance meter center to top of can;
U5168-XL-150-KK-IL-5T9W-EVE / MC0816B1150RJBT	200A	1Ø3W	150A	8 (with feed- through lugs)	OH/UG	3" Bottom KO; Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; 9" minimum clearance meter center to top of can;
U5168-XL-200-KK-IL-5T9W-EVE / MC0816B1200RJBT/ MB816B200BTS	200A	1Ø3W	200A	8 (with feed- through lugs)	OH/UG	3" Bottom KO; Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; 9" minimum clearance meter center to top of can;

≤ 200A Commercial Meter-Mains and Meter-Load Centers (Heavy Duty Lever Bypass)						
Milbank Cat Number	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
U3791N-RXL-100-IL-5T9W-EVE	200A	1Ø3W	100A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;
U3791N-RXL-150-IL-5T9W-EVE	200A	1Ø3W	150A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;
U3791N-RXL-200-IL-5T9W-EVE	200A	1Ø3W	200A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;
U5750-RXL-150-IL-EVE	200A	3Ø4W - 240V	150A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; 9" minimum clearance meter center to top of can;
U5750-RXL-200-IL-EVE	200A	3Ø4W - 240V	200A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; 9" minimum clearance meter center to top of can;
U6281-XL-100-IL-5T9W-EVE	200A	1Ø3W	100A	10 (with feed- through lugs)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;
U6281-XL-150-IL-5T9W-EVE	200A	1Ø3W	150A	8 (with feed- through lugs)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;
U6281-XL-200-IL-5T9W-EVE	200A	1Ø3W	200A	8 (with feed- through lugs)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 9" minimum clearance meter center to top of can;

320A Meter-Mains and Meter-Load Centers (Heavy Duty Lever Bypass)						
Milbank Cat Number	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
U5059-X-2-200-K3L-IL-5T9W-EVE U6585X2200K3L5T9WILEVE ⁴	320A	1Ø3W	(2) X 200A	N/A (main breakers only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;
U5890-X-2-200-K3L-IL-5T9W-EVE U6601-X-2/200-K3L-5T9-EVE ⁴	320A	1Ø3W	(2) X 200A	N/A (main breakers only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;
U5891-X-2-200-K3L-IL-5T9W-EVE U6602-X-2/200-K3L-5T9-EVE ⁴	320A	1Ø3W	(2) X 200A	10 (with feed- through lugs)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;
U5892-X-2-200-K3L-IL-5T9W-EVE U6603-X-2/200-K3L-5T9-EVE ⁴	320A	1Ø3W	(2) X 200A	22 (with feed- through lugs)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;
U6115-X-2-200-K7L-IL-EVE U6056-X-2/200-K7L-IL-EVE ⁴	320A	3Ø4W	(2) X 200A	N/A (main breakers only)	OH/UG	3" Bottom KO; Lever bypass; 17.5" minimum clearance meter center to top of can;
U6227-X-400-K3L-IL-5T9W-EVE	320A	1Ø3W	400A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;
U6229-X-400-K7L-IL-EVE	320A	3Ø4W	400A	N/A (main breaker only)	OH/UG	3" Bottom KO; Lever bypass; 17.5" minimum clearance meter center to top of can;

320A Meter-Mains and Meter-Load Centers (Heavy Duty Lever Bypass)						
Ronk Electric Cat Number	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
MSB320LE(2)-UG	320A	1Ø3W	(2) X 200A	N/A (main breakers only)	UG	3" Bottom KO; Lever bypass; Fifth terminal at 9:00 pre- wired and bonded to can; 17.5" minimum clearance meter center to top of can;

≤ 200A Residential Meter-Main and Meter-Load Center Pedestals (Horn Bypass)						
Milbank Cat Number	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
U5136-O-100S-IL-5T9W-EVE	200A	1Ø3W	100A	4	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U5136-O-200S-IL-5T9W-EVE	200A	1Ø3W	200A	4	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U5137-O-100S-IL-5T9W-EVE	200A ea (twin head)	1Ø3W	100A	4	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U5137-O-200S-IL-5T9W-EVE	200A ea (twin head)	1Ø3W	200A	4	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U6220-O-100-KK-IL-5T9W-EVE	200A	1Ø3W	100A	9	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U6220-O-200-KK-IL-5T9W-EVE	200A	1Ø3W	200A	7	UG	Horn -KK bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;

≤ 200A Commercial Meter-Main and Meter-Load Center Pedestals (Heavy Duty Lever Bypass)						
Milbank Cat Number	Socket Amp	Ø & W Config	Main Breaker(s)	Branch Spaces	OH/UG	Required EVERGY Features
U6221-O-100-IL-5T9W-EVE	200A	1Ø3W	100A	10	UG	Lever Bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;
U6221-O-200-IL-5T9W-EVE	200A	1Ø3W	200A	8	UG	Lever Bypass; Fifth terminal at 9:00 pre-wired and bonded to can; depth to allow 3" conduit entry in bottom;

⁴ NEC 2020 / UL 67 compliant model. Check local jurisdiction for requirements